# **D-Link**



## DCS-F500 VIDEO MANAGEMENT SERVER

The DCS-F500 is a smart integrated surveillance platform with video input, storage, transfer and device management functions designed specifically for digital surveillance applications. The DCS-F500 has adopted audio/video compression and decompression, embedded system, storage, network, and smart technologies and it is suitable for security surveillance scenarios such as residential areas, buildings, campus, hotels, and shopping malls etc.

#### **KEY FEATURES**


- Stability: Linux OS, dual-BIOS, redundant power
- Compatibility: Third-party IP Cameras supported with standard ONVIF
- Access: Browser/Server, Client/Server and mobile clients (both iOS and Android)
- Monitoring: 1000 device connections, up to 2000 channels of high-definition network videos
- Recording: 256 Cameras
- Management: Unified management of NVR, IPC, encoder, decoder, network keyboard, cloud devices, alarm control panel and door access control, support devices configuration import/export
- Storage: Max 16 hard disks and 2 disk enclosures; expandable up to 48 disks with 384TB storage
- Decoding: Max 16×1080P decoding outputs in three screens, expandable up to 112×1080P in 15 screens with 2 decoding cards inserted
- Service: Live view, playback, sequence, video wall, E-map, two-way audio, and alarm plan
- VCA: Support of receiving VCA alarms, configuring alarm-linkage operations, and displaying people counting statistics in reports
- Reliability: Support of HTTPS, 802.1x authentication, ARP protection, Telnet enabling/disabling, network fault tolerance, multi-IP configuration and load balancing

VIDEO MANAGEMENT	
Number of connected cameras per serve	r Device:1000 devices or 2000 channels monitoring IPC, NVR, encoder, decoder(standard/expanded), network keyboard, cloud devices, alarm control panel and door access control
Device management	Recording: 256 Camera, ONVIF Device: 200 Devices
Numbers of online users	300
Numbers of roles per user	16
Bandwidth of video input per server	512 Mbps
Bandwidth of video output per server	384 Mbps
DECODING	
Video compression	Ultra265, H.265, H.264
Decoding	4×4K@30, 16×1080p@30, 36×720p@30, 64×D1
Resolution	12MP/8MP/6MP/5MP/4MP/3MP/1080P/960P/720P/960H/D1/2CIF/CIF/QCI
Display on video wall	HDMI(×2) and VGA(×1) output; HDMI output supports 4K resolution
Audio compression	G.711
Decoding card (Optional)	Max 2 cards supported; models: F500-HDMI4 and F500-HDMI6
F500-HDMI4 decoding card	4-ch HDMI outputs, with decoding of 4*4K@60 or 8*4K@30 or 32*1080P@30 or 64*720P@30
F500-HDMI6 decoding card	6-ch HDMI outputs, with decoding of 6*4K@60 or 12*4K@30 or 48*1080P@30 or 96*720P@30
STORAGE	
HDD installation	Hot-swappable HDDs, Support 16HDDs (3.5", up to 8TB for each)
RAID mode	RAID1, RAID5, RAID6, RAID10, RAID50, RAID60
Bandwidth of video storage per server	512Mbps
Disk enclosure (optional)	Max 2 disk enclosures supported; models: F500-EN8 and F500-EN16
F500-EN8 disk enclosure F500-EN16 disk enclosure 1 / 3 / 4 / 5 / 6 / 7 / 8 / 9 / 10 / 13 / 16 / 17 / 25	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5 / 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/25 PLAYBACK	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5 / 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/25 PLAYBACK	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/29 PLAYBACK Play NVR recordings Up to 24 channels for	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5 / 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/29 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5 / 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors or multiple clients; synchronous playback up to 16 channels for single clien
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/25 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5/ 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors or multiple clients; synchronous playback up to 16 channels for single clien Intel(R) CPU
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5/ 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors or multiple clients; synchronous playback up to 16 channels for single clien Intel(R) CPU 4GB DDR3L
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5/ 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors or multiple clients; synchronous playback up to 16 channels for single client Intel(R) CPU 4GB DDR3L
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/29 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         i6xSATA interfaces, up to 8TB storage per interface         i7 32 / 36 / 64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×100M SFP optical interfaces
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB	8xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 16xSATA interfaces, up to 8TB storage per interface 5/32/36/64 window display Corridor format Up to 3 auxiliary monitors or multiple clients; synchronous playback up to 16 channels for single clien Intel(R) CPU 4GB DDR3L 100-240 VAC (with power on/off switch) Dual-power redundancy 4×10M/100M/1000M Base-T adaptive Ethernet interfaces 2×1000M SFP optical interfaces 4×USB3.0
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/29 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/1000M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×100M/1000M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1×RS-232 (RJ45), 1×RS-485 (RJ45)
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×100M/1000M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1×RS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1×RS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output Audio alarm	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1×RS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC         Buzzer
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output Audio alarm Expansion	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1×RS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/29 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output Audio alarm Expansion OTHERS	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1×RS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC         Buzzer         1×eSATA interface 2×miniSAS interfaces 2×decoding cards
F500-EN8 disk enclosure F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output Audio alarm Expansion OTHERS Power consumption	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1xRS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC         Buzzer         1×eSATA interface 2×miniSAS interfaces 2×decoding cards         50W (not including HDD)
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output Audio alarm Expansion OTHERS Power consumption Operating temperature	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single client         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/1000M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1xRS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC         Buzzer         1×eSATA interface 2×miniSAS interfaces 2×decoding cards         50W (not including HDD)       165W (including HDD)         -10°C to 55°C (14°F to 131°F)
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output Audio alarm Expansion OTHERS Power consumption Operating temperature Operating humidity	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         172/36 / 64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/100M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1×RS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC         Buzzer         1×eSATA interface 2×miniSAS interfaces 2×decoding cards         50W (not including HDD) 165W (including HDD)         -10°C to 55°C (14°F to 131°F)         10% to 90% (noncondensing)
F500-EN8 disk enclosure F500-EN16 disk enclosure 1/3/4/5/6/7/8/9/10/13/16/17/22 PLAYBACK Play NVR recordings Up to 24 channels for SYSTEM Main Processor Memory Power supply INTERFACE Network USB HDMI VGA Serial Alarm input/output Power output Audio alarm Expansion OTHERS Power consumption Operating temperature	8xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         16xSATA interfaces, up to 8TB storage per interface         5/32/36/64 window display Corridor format Up to 3 auxiliary monitors         or multiple clients; synchronous playback up to 16 channels for single clien         Intel(R) CPU         4GB DDR3L         100-240 VAC (with power on/off switch) Dual-power redundancy         4×10M/1000M/1000M Base-T adaptive Ethernet interfaces         2×1000M SFP optical interfaces         4×USB3.0         2×HDMI         1×VGA         1xRS-232 (RJ45), 1×RS-485 (RJ45)         24×alarm inputs, 8×alarm outputs         12 V DC         Buzzer         1×eSATA interface 2×miniSAS interfaces 2×decoding cards         50W (not including HDD)       165W (including HDD)         -10°C to 55°C (14°F to 131°F)



# **D-Link**

### DIMENSIONS



#### **REAR PANEL**



- (1) Grounding
- (2) 1000M SFP Interface
- (3) 1000M Ethernet Interface
- (4) RS-485/422
- (5) RS-232
- (6) USB3.0
- (7) eSATA Interface
- (8) Audio Input
- (9) HDMI Output
- (10) Audio Output
- (11) VGA Output

(12)miniSAS Interface
(13) Power Button
(14) Reset
(15) Alarm Input
(16) Alarm Output
(17) 12V Power Output
(18) Decoding Card (optional)
(19) AC Power Module 1
(20) AC Power Module 2 (optional)
(21) Decoding Card (optional)

## DCS-F500