



Optic Fiber Adapter Panels

D-Link offers comprehensive range of adapter panel which enhance installation flexibility and convenience. The panel can be loaded with adapters and can snap in for installation and can be removed easily for future changes. Blank fiber adapter panels reserve fiber adapter panel space for future use. All fiber adapter panels snap quickly into the front of fiber optic patch panels and enclosures for easy network deployment or moves, adds and changes.

FEATURES

- Cold rolled steel materials
- Available in 6~24 holes (according to the type of adapters)
- Offer type of 175,109 size module panels, other dimension and type according to customers' request
- Suitable for FC, LC, SC, ST adapters
- Panel fastener to hold adapter panels securely in place
- Ideal for simple moves, adds and changes

APPLICATIONS

- Installation and management of fiber optic patch cords and pigtailed
- Used with rack mount, both fixed and sliding fiber optic patch panel and wall mount distribution box
- High-density fiber optic network application

SPECIFICATIONS			
PARTS	MATERIAL	DIMENSION	Remarks
Panel	Steel, 1.5mm Thickness	175x37mm (WxH) 109 x35.4mm (WxH)	Black, Beige
Panel Fastener	PC	175 panel: 8.2mm 109 panel: 6.4mm	2 Pieces / panel, Black

Product No.	Description
NPL-FXXSC-06	Unloaded Adapter Panel Accepts 6 Simplex SC/6 Duplex LC Adapters
NPL-FXXLC-06	Unloaded Adapter Panel Accepts 6 Simplex LC Adapters
NPL-FXXSC-12	Unloaded Adapter Panel Accepts 12 Simplex SC/12 Duplex LC Adapters
NPL-FXXFC-12	Unloaded Adapter Panel Accepts 12 Simplex FC Adapters
NPL-FXXST-12	Unloaded Adapter Panel Accepts 12 Simplex ST Adapters
NPL-FXDSC-03	Unloaded Adapter Panel Accepts 3 Duplex SC Adapters
NPL-FXDSC-06	Unloaded Adapter Panel Accepts 6 Duplex SC Adapters
NPL-FXDSC-12	Unloaded Adapter Panel Accepts 12 Duplex SC Adapters